

4½ Digit Multimeter



Features

- Economic and full functions
- True 4½ digits with 19999 count
- Measures DCV, ACV, DCA, ACA, resistance, capacitance, frequency and temperature
- Tests diode and continuity
- Built-in math operations
- Standard interface of USB device

Technical Specifications

	Range	Best Accuracy
Basic Functions		
DC Voltage	200mV / 2V / 20V / 200V / 1000V	±(0.03% + 15)
AC Voltage	2V / 20V / 200V / 750V	±(0.4% + 50)
DC Current	200µA / 2000µA / 20mA / 200mA / 10A	±(0.1% + 30)
AC Current	200µA / 2000µA / 20mA / 200mA / 10A	±(0.7% + 30)
Resistance	200Ω / 2KΩ / 20KΩ / 200KΩ / 2MΩ / 20MΩ	±(0.3% + 40)
Capacitance	20nF / 200nF / 2µF / 20µF / 200µF / 2mF / 20mF	±(1.0% + 20)
Frequency	20Hz / 200Hz / 2000Hz / 20kHz / 200kHz / 2MHz / 20MHz / 200MHz	±(0.1% + 8)
Temperature	-200 ~ 800°C	±(1% + 30)
Other Functions		
Display Count	19999	
Auto Range	✓	
Diode	✓	
Continuity	✓	
Null	✓	
Trigger	✓	
Math	dB, dBm	
General Characteristics		
Safety	Conform to IEC61010-1, CAT I 1000V / CAT II 600V	
Interface	USB Device	
Power	110V / 220V (±10%), 50Hz (±5%), 8VA	
Dimensions	102 x 256 x 306 mm	
Weight	2 Kgs	
Standard Accessories		
Power Cord	1	
Test Leads	1	
Alligator Clip	1	
Temperature Probe	1	
CD (User's Guide)	1	

WE PURSUE A POLICY OF CONTINUOUS DEVELOPMENT AND PRODUCT IMPROVEMENT. THUS THE SPECIFICATIONS IN THIS DOCUMENT AND THE LOCATION OF CONTROLS ON THE FRONT PANEL MAY BE CHANGED WITHOUT NOTICE.